

SENSOR PRODUCTS SELECTION MANUAL



Wenzhou Gtric Technology Co., Ltd.
TEL:0577-62734566
Web:<http://www.gtric.com>
Mail: yaohaofeng@gtric.com

Company introduction

Wenzhou Gtric Technology Co., Ltd. is located in Yueqing IoT sensors Park, which covers 5,000 square meters, with over 100 employees. We are focuses on intelligent manufacturing and industrial automation, our main businesses are sensors, encoders, button switch, coupling, expansion set and other industrial automation products, providing standard and individual products and solutions for customers.

Our products cover over 20 series, 1000specificatison, which have passed CCC, CE, UL, ISO9001 certification as well as EU RoHS Environmental Directives.

Based on our technical advantages, Gtric can provide industrial automation solution according to customers' requirements.

**We support OEM & ODM, if you need
please feel free to contact us**




Sensor characteristics

GTRIC®

✧ Series and parallel connection of proximity switch


OR connection (NPN and PNP types can be used mixed) series When the proximity switch is OR connected, the action of any proximity switch can drive load. The quantity of the proximity switches depends on the sum of leakage current. More connections are available given that it doesn't affect the loading action.



OR connection of NPN output OR connection of PNP output

✧ AND connection (series)


When the proximity switch is AND connected, the action of all proximity switches can drive load. The quantity of the proximity switches depends on the sum of saturation voltage. More connections are available given that it doesn't affect the supply voltage of the proximity switch. The response frequency of the proximity switch is the accumulation of initialized reset of various proximity switch.



NPN connection of AND output PNP connection of AND output

✧ Series and parallel connection of proximity switch

AND connection (series) NPN, PNP mixed—use



Promixity switches matters need attention

✧ Cautions when connected or disconnected with the power supply

When connecting the proximity switch with the counter and the programmable controller, there isn't any problem because of the built-in initialized reset circuit. Please avoid the conditions mentioned below

The detection object lies around the detection distance of the proximity switch; For DC voltage type and DC switch type, when power supply is turned on (turned off), time constant rises (drops) greatly; There is self-excitation and noise when the AC switch type proximity switch is power-on (off)

✧ Capacitor, light load

The proximity switch can't have the capacitor or light that has larger jumping current as the load directly connected to be connected through a relay or series connected with a current-limiting resistance. The peak current set by current-limiting resistance R is within the load current of the proximity switch; Make sure to connect through load.

Supply voltage V

Peak load current value of proximity switch mA

≤R(KΩ)

Allowable loss of resistance R (W)


Supply voltage V²

≤R(KΩ)


× 2 times above

✧ Installation notice of proximity switch


Don't use it in the open air, and use a protective cover, if necessary.




Don't knock the detection surface with hard objects and use a protective cover, if necessary.




Don't use it in the environment with corrosive objects.




Don't fasten it with a big force, but fasten it with spring washer




The proximity switch must be equipped individually with metal flexible pipe, and don't make it with the electric line and power line in the same metal flexible pipe




Don't stretch the power line of the proximity switch with a big force.



LR Series Inductive Proximity Sensor Sensing Distance Diagram




FR Series inductive proximity sensor sensing Distance Diagram



Matters needing attention

When detecting objects of different materials, the actual sensing distance of the proximity switch is different, as shown in the figure below



- ✧ With overload short circuit, reverse connection protection, surge absorption IP67 protection level
- ✧ It has the advantages of water resistance, oil resistance, high temperature resistance, etc. 360° full surround green LED display working status
- ✧ More intuitive and obvious Ultra-long-distance detection, making products more diversified



Selection Guide

GTRIC®

FR	30	—	20	N	1	
①	②		③	④	⑤	⑥
① Model : LR: Inductive Sensor、CR: Capacitive Sensor、FR: long Distance Inductive Sensor						
② DIA. of sensing side : Number: DIA. of sensing side (unit:mm)						
③ Sensing distance : Number: Sensing distance (unit:mm)						
④ Powersupply : N: NPN 10-30VDC 3-wire、P: PNP 10-30VDC 3-wire、D: 10-30VDC 2-wire A: 90-250VAC 2-wire						
⑤ Control output : 1:Normallyopen、2:Normally closed						
⑥ Connection : Nomark: Cable type、P: Connector type、WP: Cable connector type						


Specifications

GTRIC®

Specifications						
Model	DC 3-wire NPN.NO	FR30-20N1	FR30-25N1	FR30-40N1	FR30-20N1-P	FR30-25N1-P
	DC 3-wire NPN.NC	FR30-20N2	FR30-25N2	FR30-40N2	FR30-20N2-P	FR30-25N2-P
	DC 3-wire PNP.NO	FR30-20P1	FR30-25P1	FR30-40P1	FR30-20P1-P	FR30-25P1-P
	DC 3-wire PNP.NC	FR30-20P2	FR30-25P2	FR30-40P2	FR30-20P2-P	FR30-25P2-P
	DC 2-wire NO	/	/	/	/	/
	DC 2-wire NC	/	/	/	/	/
	AC 2-wire NO	/	/	/	/	/
	AC 2-wire NC	/	/	/	/	/
Mounting		Flush	Non-Flush	Non-Flush	Flush	Non-Flush
Sensing distance		20MM+10%	25MM+10%	40MM±10%	20MM±10%	25MM±10%
Setting distance(Sa)		0-18MM	0-22.5MM	0-36MM	0-18MM	0-22.5MM
Hysteresis		≤10%				
Standard sensing target		30*30*1MM (iron)				
Supply voltage		DC:10-30VDC； AC: 90-250V				
Leakage current		≤0.6mA				
Response frequency(F)		500Hz (DC) 25Hz (AC)				
Consumption current		DC3-wireNPNPNP：≤10mA;DC2-wire：≤3mA;AC2-wire：≤2mA				
Load current		200mA				
Voltage drop		≤2.5V				
Circuit protection		Short-circuit,overload,reversepolarityprotection				
Output indicator		GreenLED				
Ambient temperature		-20~+70℃				
Shock		500m/s(50G)ineachX,Y,Zdirectionfor3times				
Vibration		1mm amplitudeatfre quency10~55Hz(for1min) ineachX.Y Zdirection for 2hours				
Protection degree		IP67(IECstandards)				
Connection		2mPVCcable		M12connector		
Material		Nickel-copperalloy				
Sensing side		PBT				

Dimension

GTRIC®





GTRIC[®]

Wenzhou Gtric Technology Co., Ltd.

Wenzhou Gtric Technology Co., Ltd.
TEL:0577-62734566
Web:<http://www.gtric.com>
Mail:yaohaofeng@gtric.com